# SENCON

# Die Protection Sensors

9-27X-03 series



**THE BEST PROTECTION** — Given the substantial investment you've already made in your tooling systems, it only makes sense to fit the very best protection. That's why leading can makers worldwide insist on Sencon Die Protection Sensors.

## DIE-SHOE MOUNTING Model 9-275-03



Designed to work with tooling systems which utilize a sensor positioned in the die-shoe behind the cup drop

# GUIDE-BAR MOUNTING Models 9-276-03, 9-278-03



Some tooling systems incorporate sensor mounts directly in the guide between cup lanes. These sensors are ultra-slim and well protected by the guide bar itself. Special field design allows sensors to reliably detect targets without being affected by guide bars. The ultra-slim shape of the 9-278-03 Sensor makes it useful in other applications where lack of space precludes the use of a conventional sensor.

# **ENSURE THAT ALL CUPS HAVE DROPPED AND CLEARED THE DIE AREA IN CUPPING PRESSES**

Sencon's custom design for effective and reliable performance. Three key features set these sensors apart from the competition:

## **UNIQUE FEATURES**

Specially shaped housings

Compact size sensors fit between lanes

Carefully designed sensing field profiles


This unbeatable combination enables:

## **BENEFITS**

Discrete, secure and quick installation

Many years of reliable, uninterrupted service

**Tooling Protection** 



| FEATURES                     |                    |                                    |                                  |                         |                            |            |          |
|------------------------------|--------------------|------------------------------------|----------------------------------|-------------------------|----------------------------|------------|----------|
| Cable Exit<br>Back (conduit) | Cable Exit<br>Side | Actuation<br>Point<br>Aluminum Cup | Actuation<br>Point<br>Steel Cup  | Supply Voltage<br>Range | On/Off<br>Response<br>Time | Case Style | Sensor   |
| •                            |                    | 0.70" ±0.025" 17.8 mm ±0.635 mm    | 0.925" ±0.025" 23.5 mm ±0.635 mm | 10.5 to 40 VDC          | ON <1.0 ms<br>OFF <3.0 ms  | D          | 9-275-03 |
|                              | •                  | 0.58" ±0.025" 14.7 mm ±0.635 mm    | 0.83" ±0.025" 21.1 mm ±0.635 mm  | 10.5 to 40 VDC          | ON <1.0 ms<br>OFF <3.0 ms  | E          | 9-276-03 |
|                              | •                  | 0.50" ±0.025" 12.7 mm ±0.635 mm    | 0.62" ±0.025" 15.7 mm ±0.635 mm  | 10.5 to 40 VDC          | ON <1.0 ms<br>OFF <2.0 ms  | F          | 9-278-03 |