

MARINE DSC/VHF RADIO TELEPHONE

- Compliant with DSC performance standard and GMDSS regulation according to ITU and IMO.
- Compact size and light weight for easy installation.
- Over 160 characters with information in one large LCD.
- Class A type DSC/VHF for GMDSS built—in dedicated receiver CH70.

Smaller Size !! Improved Performance !!





STR-6000A









STR-6000A

FEATURES

- ▶ Includes all channels specified in ITU-RR(NOAA Weather channel)
 ▶ Latitude/Longitude display function when connected with GPS.
- ▶ DUAL/TRIPLE WATCH function and TAG SCAN function built—in.
- ▶ 20 MMSI number in 2 groups—MMSI number save, edition and call function.
- Over 160 characters can be seen in one large LCD.
- ▶ Priority selection of Ch.16 and adoption of noise free mic.
- Compact & light design for any—where installation.

SPECIFICATIONS

■ GENERALS

- TX Frequency: 156.025~157.425MHz ▶ RX Frequency: 156.050~163.275MHz
- ► Communication Mode: Simplex and Semi-Duplex
- Channel Number: 183 channels (ITU 55, USA 57, CAN 61, WEA 10)
- ▶ Type of Emission: FM(16K0G3E), DSC(16K0G2B)
- Freq. Stability: ±10 ppm(-20° ~ +60°)
- ► Antenna Impedance: 50Ï
- Consumed Currency (13.6V): TX high 5.5A max Max. Audio 1.5A max
- ▶ Power Supply : DC 24V (DC 18 ~ 31.2V) AC 100 ~ 120V, AC 200 ~ 240V

■ TRANSMITTER UNIT

- ► Antenna Output: HIGH/25W, LOW/1W
- ▶ Starting Mode: SYNTHESIZER mode
- ▶ Modulation Mode: VARIABLE REACTANCE FREQUENCY MODULATION
- Occupancy Band Width: Within: 16KHz
- Max. Freq. Deviation: ±5KHz
- ▶ Spurious Emission: Over 70dB
- ► MIC Input Impedance: 2kΩ

■ RECEIVER UNIT

- ▶ Receiving Mode: DOUBLE CONVERSATION SUPER HETERODYNE
- ► Receiving Sensitivity: 0.32 ¼ (20dB SINAD), 0.22 ¼ (12dB SINAD)
- ► Squelch Sensitivity: Less than 0.22 μV
- ► Spurious Emission: Less than -70dB

- ▶ Residual Noise Level: Less than -40dB
- ► Audio Output: 4.5W / 4Ï

■ DSC WATCH KEEPING RECEIVER

- ▶ Receiving Freq.: 156.525MHz
- ▶ Radio Wave Mode: G2B
- ►DSC Modulation Speed: 1200baud(Within 600Hz ±30×10⁻⁶ Freq.)
- DSC Modulation Mode: FSK
- ►DSC Modulation Quotient: Within m=2±10%
- ► Adjacent Channel Select: Less than 10⁻² Bit error rate
- Spurious Response: Less than 10⁻² Bit error rate
- ►Inter-Modulation Response: Less than 10^2 Bit error rate
- ▶ Dynamic Range: Less than 10² Bit error rate

COMPONENTS

■ STANDARD


- ► Hand MIC(SM-6000)
- Speaker (SS-6000)
- Installation Material
- Instruction Manual

■ OPTION


- ► Transceiver Unit(STR-6000A) ► Whip Antenna (SAN-150)


 - Power Supply (SP-580AD)
 - Bracket for Flushing Type(SMB-60)
 - **EMG LIGHT**
 - Printer(DPU-414)

CONFIGURATION



DIMENSIONS & INSTALLATIONS







SAMYUNG ENC Co.,Ltd.

Head Office: 1123-17, Dongsam-Dong, Youngdo-Gu, Busan, Korea, 606-083 Tel: 82-51-601-5532(Rep.) Fax: 82-51-413-4446

A/S Center: 65-20, 2-Ga Namhang-Dong, Yungdo-Gu, Busan, Korea, 606-032

Tel: 82-51-601-5570~4(Rep.) Fax: 82-51-416-5515 Http://www.samyungenc.com



KS Q ISO 9001:2015 SMI-22160

