# **Or** Sense PSD25 Series Pressure Switches



### **Features**

- Compact pressure switch features simple setup using mechanical adjustment dials
- Extremely durable housing with 316 stainless steel process connection
- No moving parts ensure long-term stability without setpoint drift
- LEDs indicate switching and operating status
- Complementary switching outputs (N.O./N.C.), DC
- Easy set-up dials
- Vibration and shock-resistant

#### **Agency Approvals**

- cULus, File number E320431
- CE
- RoHS

MOHS CULUS CE

ProSense Series Pressure Sensors								
Part Number	Description	Pcs/Pkg	Wt(lb)	Price	Cable Assemblies			
PSD25-0P-0145H	Pressure switch, DC, PNP NO/NC, 7.5 to 145 psig range, 1/4" NPT male port	1	0.21	\$89.00	CD12L-0B-020-A0 CD12L-0B-020-C0			
PSD25-0P-1450H	Pressure switch, DC, PNP NO/NC, 75 to 1450 psig range, 1/4" NPT male port	1	0.21	\$89.00	00 CD12M-0B-070-A1 CD12M-0B-070-C1			
PSD25-0P-5800H	Pressure switch, DC, PNP NO/NC, 290 to 5800 psig range, 1/4" NPT male port	1	0.21	\$89.00				
Accessory								
PSD-CV	Transparent plastic protective cap for PSD series	1	0.01	\$3.00	PSD Series Sensors			

Note: Check the chemical compatibility of the sensor's wetted parts with the medium to be measured.

ProSense PSD25 Series Technical Specifications						
Operating Voltage	9.6 to 32 VDC					
Connection Pin Material	Gold-plated					
Output Maximum Load Current	500 mA - See Setting and Operation Guide on following page.					
Current Consumption	< 25 mA					
Switching Frequency	100 Hz					
Setting Accuracy of Switch Points	< ± 2.5% of full range (limit point calibration)					
Repeatability	< ± 0.5% of full range					
Temperature Drift	$<$ $\pm$ 0.5%, of full temperature range/10 K;32 to 176°F (0 to 80°C).					
Housing Material	PBT (Pocan); PC (Makrolon); FPM (Viton); stainless steel (316S12)					
Materials (wetted parts)	Stainless steel (316S12)					
Operating Temperature	–13 to 176°F (–25 to 80°C)					
Medium Temperature	–13 to 176°F (–25 to 80°C)					
Storage Temperature	-40 to 212°F (-40 to 100°C)					
Protection	IP 67					
Protection Class	Class III 🐵					
Insulation Resistance	> 100 MΩ (500 VDC)					
Shock Resistance	50g (DIN / IEC 68-2-27, 11ms)					
Vibration Resistance	20g (DIN / IEC 68-2-6, 10 - 2000 Hz)					
EMC						
EN 61000-4-2 ESD	4 kV/8 kV AD					
EN 61000-4-3 HF Radiated	10 V/m					
EN 61000-4-4 Burst	2 kV					
EN 61000-4-6 HF Conducted	10 V					

Applications (Type of Pressure: Relative Pressure, Liquids and Gases)								
Part Number	Setpoint Scale	Resetpoint Scale	Permissible Overload Pressure	Bursting Pressure				
	Bar (Psig)	Bar (Psig)	Bar (Psig)	Bar (Psig)				
PSD25-0P-5800H	20 to 400 (290 to 5800)	12 to 392(175 to 5685)	600 (8700)	1600 (23200)				
PSD25-0P-1450H	5 to 100 (75 to1450)	3 to 98 (50 to 1420)	200 (2900)	1000 (14500)				
PSD25-0P-0145H	0.5 to 10 (7.5 to 145)	0.3 to 9.8 (5 to 142)	25 (362)	300 (4350)				

Note: Full vacuum permissible




WARNING! AVOID STATIC AND DYNAMIC OVERPRESSURE EXCEEDING THE GIVEN OVERLOAD PRESSURE.

EXCEEDING THE BURSTING PRESSURE FOR EVEN A SHORT TIME CAN CAUSE DESTRUCTION OF THE UNIT AND POSSIBLE INJURIES!


# Or Sense PSD25 Series Pressure Switches

#### **Switch Dimensions**



Note: tightening torque 25 Nm (18.4 lb-ft)


#### **Switch Cover Dimensions**



Dimensions shown mm [inches]

See our website www.AutomationDirect.com for complete Engineering drawings.

### **PSD25 Wiring Diagrams**



**Cable Assembly Wiring Colors:** 

Pin 1 - Brown


Pin 2 - White

Pin 3 - Blue

Pin 4 - Black

Note: wiring colors are based on AutomationDirect CD12L and CD12M 4-pole cable assemblies.

## **Setting and Operation**



- 1. locking ring
- 2. setting rings (manually adjustable after unlocking)
- 3. LED green: supply voltage O. K.
- 4. process connection 1/4" NPT; tightening torque 25 Nm
- setting marks
- 6. LED yellow: Set value reached, OUT1 = ON / OUT2 = OFF
- 7. internal thread M5
- Minimum distance between Set and Reset = 2% of the final value of the measuring range.
- To obtain the setting accuracy: Set both rings to the minimum value, then set the requested values.